



Smart Home og telefoner    Smart Home

## KX-HNS102 Bevegelsessensor

Colour	White	
Frequency Range	DECT: 1.88 GHz - 1.90 GHz	
Sensor Detection Method	Pyroelectric infrared sensor (heat sensor)	
Heat Sensor Detection Range	Horizontal: approx. $\pm 45^\circ$ /Vertical: approx. $\pm 10^\circ$ /Distance:/approx. 5 m (When the sensitivity switch is in the "HIGH" position)/approx. 2.5 m (When the sensitivity switch is in the "LOW" position)/ <sup>*</sup> When the surrounding temperature is approx. 25 °C.	
Sensor Sensitivity Select Switch	Yes (High / Low)	
Status Indication	LED (Red/Green)	
Setup Button	One Push Pairing button	
Power Source	AA (LR6) Alkaline battery (2 x 1.5V)	
Battery Life	Up to 1 year/ <sup>*</sup> When motion is detected 50 times a day and the surrounding temperature is approx. 25 °C.	
Wall Mount	Yes	
Operating Conditions	0 °C – 40 °C	
Dimensions/ Weight	Dimensions (H x W x D)	Approx. 72 mm x 73 mm x 39 mm <sup>*1</sup> /Approx. 72 mm x 73 mm x 61 mm <sup>*2</sup> / <sup>*1</sup> With the rear cover attached./ <sup>*2</sup> With the wall mounting adaptor attached.
	Weight	Approx. 70 g <sup>*1</sup> <sup>*3</sup> /Approx. 77 g <sup>*2</sup> <sup>*3</sup> / <sup>*1</sup> With the rear cover attached./ <sup>*2</sup> With the wall mounting adaptor attached./ <sup>*3</sup> Excluding the batteries.

Copyright © 2017 Panasonic All rights reserved.